Comparative Analysis of Efficient Designs of D- Latch using 32nm CMOS Technology

Tanusha Beni Vyas¹, Shubhash Chandra²

¹PG. Scholar, ²Assistant Professor

^{1,2}Information and Technology, Rajasthan College of Engineering for Women, Jaipur, Rajasthan, India

How to cite this paper: Tanusha Beni Vyas | Shubhash Chandra "Comparative Analysis of Efficient Designs of D- Latch using 32nm CMOS Technology" Published

in International Journal of Trend in Scientific Research and Development (ijtsrd), ISSN: 2456-6470, Volume-3 | Issue-5, August 2019, pp.1785-1788,



https://doi.org/10.31142/ijtsrd26707

Copyright © 2019 by author(s) and International Journal of Trend in Scientific Research and Development Journal. This is an Open Access article distributed

under the terms of the Creative Commons Attribution License (CC



(http://creativecommons.org/licenses/by /4.0) ABSTRACT

In this paper we have proposed various efficient designs of low power D-latch using 32nm CMOS technology. We have designed and simulated these circuits in HSpice simulation tool. In this simulation we have modified W/Lratio of each transistor in each circuit. We have taken power supply of 0.9V. We have calculated average power consumed propagation delay and power delay product.

KEYWORDS: Latch, CMOS, Clock, Power Delay Product, MOSFET

1. INTRODUCTION

Developments in large scale integration resulted in millions of transistors placed on a single chip for execution of intricate circuitry. Due to this placing of large no of transistors within a small area resulted in more heat dissipation and power consumption. To solve these problems many research were carried on and solutions were proposed such as by decreasing the power supply voltage, switching frequency and capacitance of transistor. Maximum number of VLSI related applications such as DSP, image & video processing and microprocessors, widely uses logic gates and arithmetic circuits. Operations such as AND, OR, addition, subtraction, and multiplication are usually used by these circuits. The building blocks of maximum digital circuits are logic gates, whereas in arithmetic circuits, 1-bit full adder cell is widely used. Therefore improving their execution is vital for improving the overall module performance.

Development on and 2. D-Latch

Due to fast development in mobile communication and computation technology demand for building of low-power VLSI systems has come forth. The technology related to battery does not progress at the same rate as that of microelectronics. Thus for the mobile systems a fixed amount of power is available. Thus, more constraints are being faced by the engineers such as: high speed, high throughput, small silicon area, and at the same time, low- power consumption. Therefore great interest was shown for designing of lowpower, high performance adder cells.

Limitation due to power dissipation can be represented by two methods. The former one is related to cooling while realizing high performance systems. Large amount of energy is dissipated from high-speed circuits in a short amount of time resulting in significant amount of heat. The produced heat requires to be removed from the package on which integrated circuits are attached. If the package cannot amply disperse this heat or if the requisite thermal components are too costly for the application heat removal may become a limiting factor. The later one relates to failure of high-power circuits due to the growing acceptance of portable electronic devices. Batteries are used as a power source in applications such as Laptop computers, portable video players and cellular phones. These devices require recharging after being operational for a limited time of operation. To lengthen the battery life, low power procedure is necessary in integrated circuits.

The one-bit digital storage element plays a fundamental role in digital signal processing circuitry. The D-latch whose waveforms are shown in Figure 1 is such a device: it is a memory element having at least two inputs, namely a clock signal {CLK} and a data signal (D) and an output (Q) (and often its complement). The device is 'transparent' duringone of the clock levels the transparent phase during which the output Q follows the input D. But when the clock level is complemented to its isolation phase the logic level presentat D is frozen at Q, which remains in that state until CLK returns to its transparent phase. D-latches are categorized as being 'positive' or 'negative', depending upon the logic level of the transparent phase.



International Journal of Trend in Scientific Research and Development (IJTSRD) @ www.ijtsrd.com eISSN: 2456-6470

3. PROPOSED WORK

We have designed six types of efficient circuit of D-Latch using MOSFET which consumes less average power. All circuits are designed using 32nm CMOS technology at 5 GHz. Power supply is 0.9V. All designs are shown below.



From fig. 2, it is the simplest method to demonstrate the working of D-Latch. When clock (CLK) is high mosfets M3 & M4 conduct and passes the input (D) further and M5, M6 invert the data which is again inverted by M11 & M12 to get the same data. At this instant data is stored and latched by M7, M8, M9 & M10. Now if the clock is low, whatever is the input does not pass further, only previous latched data gets passed to the output because of conduction of M9 & M10.



From fig. 3, when clock (CLK) is high, M3, M4 conducts and input D passes to the output. This output also goes to M7, M8, M9, M10 and gets inverted. Now if the clock is low, inverted data switches on M11, M13 (if D = '1') & M12, M14 (if D = '0') and keeps the previous data at the output terminal.

Similarly some other circuits of D-latch are also designed using 32nm CMOS library which are shown as follows:





International Journal of Trend in Scientific Research and Development (IJTSRD) @ www.ijtsrd.com eISSN: 2456-6470

10

Graph0

(V) : t(s)

4. EXPERIMENTAL RESULTS

Now in this section, we have shown output graphs for each circuit design operated at frequency of 5 GHz. We have provided clock signal of frequency 5 GHz and a data signal to



International Journal of Trend in Scientific Research and Development (IJTSRD) @ www.ijtsrd.com eISSN: 2456-6470





Fig-13: Output of D-latch design 6

Table 1 depicts the comparison between these designs of Dlatch according to different parameters. These simulations also show better performance of these circuits as compared to circuits and results described in other literatures

$1 a D C I_1 G D H D D H D C C W C C H G C S C H D I A C H$

Design No.	No. of Transistors	Average Power (µW)	Delay Time (ps)	PDP (fJ)
1	12	0.38	319.5	0.12
2	14	0.35	306.04	0.11
3	7	0.13	12.44	0.002
4	6	0.07	8.06	0.006
5	6	0.16	2.44	0.004
6	12	0.26	21.5	0.005
Ref [5]	14	1.05	38.10	0.040

5. CONCLUSIONS

In conclusion, it has been observed that design of D-latch based on sleep transistor shows better performance than stacked inverter. All the simulations are performed n HSpice simulation tool using 32nm CMOS library at power supply of 0.9V for frequency of 5GHz. These designs are working satisfactorily at high frequencies.

REFERENCES

[1] J. B. Kuo, J. Lou, "Low Voltage CMOS VLSI circuits", John Wiley & Sons, 1999.

[2] J. M. Rabaey, "Digital Integrated Circuits", Prentice Hall, 1996.

- [3] K. Roy and S. Prasad, Low Power CMOS VLSI Circuit Design.
- [4] Shankar Kumar Vijay, Sanjay Kumar Jaiswal, Kumkum Verma, "Design and analysis of CMOS Inverter and D
- Latch MCML Inverter", International Journal of Advanced Trends in Computer Science and Engineering, 2012.
- [5] Sumitra Singar and P.K. Ghosh, "Unique Robust Fault Resistant D-Latch for Low Power Applications", IEEE, 2017.
- [6] Saeideh Shirinzadeh, Rahebeh Niaraki Asli, "Design and performance evaluation of a low cost Full Protected CMOS Latch", IEEE Computer Society, 2013.
- [7] Saeideh Shirinzadeh, Rahebeh Niaraki Asli, "High Efficiency Time Redundant Hardened Latch for Reliable Circuit Design", Springer, 2013.
- [8] Sumitra Singar, N. K. Joshi and P.K.Ghosh, "Novel Fault Resistant D-Latch for Low Power VLSI Design", International Journal of Engineering and Manufacturing Science, 2017.
- [9] Kanika and Pawan Kumar Dahiya, "Analyzing the Impact of Sleep Transistor on SRAM", IOSR Journal of VLSI and Signal Processing, 2017.
- [10] Ankita Nagar and Vidhu Parmar, "Implementation of Transistor Stacking Technique in Combinational Circuits", IOSR Journal of VLSI and Signal Processing, 2014.

Fig-12: Output of D-latch design 5